

# Lever Bypass Single Position

320 Amps | 4 Terminals | Ringless

**1 1**  
320 AMP  
LEVER  
BYPASS  
SOCKETS







U4702-X



U1797-O-K3L-K2L



U4257-X



## 320 Amps | 4 Terminals | Ringless | Lever Bypass | Single Position

Catalog Number	Terminals	Service	Hub	Connectors CU/AL		Bypass	Dimensions			Knockouts		
				Line	Load		D"	W"	H"	1	2	3
U4702-X	4	OH	C.P.	3/8" x16 Studs	3/8" x16 Studs	Lever	4 7/8	15	28 1/4	3	1/4, 1/2	1/4
U1797-O-K3L-K2L	4	UG	Blank	(1) #4-600 or (2) 1/0-250	Twin #6-350	Lever	4 7/8	15	30	3	1/4, 1/2	1/4
U6047-O-K3L-K2L	4	UG	Blank	(1) #4-600 or (2) 1/0-250	Twin #6-350	Lever	4 7/8	15	30	3	1/4, 1/2	1/4
U4257-X	4	UG	C.P.	3/8" x16 Studs	3/8" x16 Studs	Lever	6 1/2	19	34 1/8	4	1/4, 1/2	—

### Notes

- **Hubs:** For proper hub selection, see the hub suffix chart on the accessories page.
- **Lever Bypass:** The lever supplies clamping action and operates bypass device.
- **Fifth Terminal:** For field installed fifth terminal, order **K3865**.
- **Isolated Neutral:** For field-installed isolated neutral, order **K5979** for **U4702**, **K5978** for **U1797** and **U6047**, and **K5977** for **U4257**.
- **Connectors:** Studded products are supplied with 3/8" -16 hex head nuts with Belleville washers. For connector lug kits, order as extra from chart in accessories section. Separate lug kits are required for line and load.
- **U6047-O-K3L-K2L:** This unit is a right-side wireway design.

Utility requirements for this equipment may vary. Always consult the serving utility for their requirements before ordering or installing equipment.

