DURACELL® SLA Batteries **ULTRA**



Duracell® Ultra Deep Cycle Batteries are designed to achieve maximum cycles throughout the life of the battery. Duracell® Ultra Deep Cycle Batteries maintain their high capacity with a design that is resistant to deep discharge.

Whether you are on the golf course, in the boat or working on the warehouse floor, you can count on Duracell® Ultra Deep Cycle Batteries to keep you running.



Wheelchair/Mobility, Riding Toys, Fishing Equipment, Floor Scrubbers, Golf Carts and more.









DURACEL



Features:

- At 14% lower cost per cycle than GEL and 25% lower than general purpose AGM, Duracell® Ultra Deep Cycle Batteries offers the lowest cost per cycle of any SLA battery type.
- Specific grid structure and thicker plates provide longer cycling capabilities than that of conventional AGM batteries.
- Increased cycle life over standard AGM batteries in deep cycle applications.
- The unique design construction and sealing techniques of the Duracell® Ultra battery guarantee leak-proof operation regardless of the battery's position with no adverse effect on its capacity or service life.
- Duracell® Ultra batteries are manufactured in compliance with the quality management system standard of ISO 9001.

Sealed Lead **Acid**



Maintenance Free



Spill Proof Design



1 Year Warranty



Stringent Quality Control



PROJECT NAME:
CATALOG #
BATTERY TYPE
NOTES

Deep Cycle

Battery	Volts	Capacity Ah (20Hrs)	Dimensions (LxWxH Inches)			Terminal Type	Group Size	Weight (Lbs.)
DURDC12-5F	12V	5AH	3.54	2.76	3.98	F1, T1	-	53
DURDC12-14F2	12V	14AH	5.96	3.93	3.82	F2, T2	-	3.9
DURDC12-14NB	12V	14AH	5.96	3.93	3.82	NB, J	-	39
DURDC12-26NB	12V	26AH	6.54	6.89	4.92	NB, J	-	39
DURDC12-20NB	12V	20AH	7.1	3	6.51	NB	U1	-
DURDC12-35J	12V	35AH	7.67	5.13	7.09	J	-	20.62
DURDC12-55C/FR-F	12V	55AH	9.02	5.43	8.19	С	-	15.21
DURDC12-55P	12V	55AH	9.375	5.5	9.25	Р	-	9.48
DURDC12-80P	12V	80AH	10.24	6.65	8.98	Р	-	9.48
DURDC12-100P	12V	100AH	12.09	6.65	8.31	Р	-	63

Charging, Maintenance, and Storage Tips



Recharge after each use and store battery fully charged



Do not store in a discharged state. Charge batteries every couple months



Overcharging kills batteries



Undercharging shortens battery life



Disconnect charger once fully charged





Check battery for corrosion or deformation



Store in cool, dry place (68°F is best)

SLA Terminal Types

















Visit www.batteriesplus.com for warranty information

